

1

### Analogue Connections

- 4 X RCA CONNECTIONS
- 3.5MM AUX INPUT
- REC OUT

2

### Power and Precision

- 25W PER CHANNEL
- ANALOGUE FILTERING

3

### Adjustable Sound

- BASS ADJUSTMENT
- TREBLE ADJUSTMENT
- BALANCE CORRECTION

### Affordable Sound Quality

Offering 25 watts of power per channel in a great value package, the AXA25 features a 3.5mm aux input on the front for smartphones and four analogue inputs on the back panel for connecting all your sources.



### Demonstration Tracks

At Cambridge Audio we use our ears constantly, both as passionate music lovers and audio professionals looking for test examples. We test our products with all types of content and the following suggestions are our picks for a great demo experience for your customers.

1

#### SHE CRIES YOUR NAME

by **BETH ORTON**

Trailer Park (1996)

Beth Orton's "She Cries Your Name" through the AXA25 begins with a detailed violin introduction and carries her characteristic vocals throughout the song with a musicality rarely seen with products at this end of the market.



2

#### FUTURE ME HATES ME

by **THE BETHS**

Future Me Hates Me (2018)

New Zealand's The Beths have taken their history lessons from the likes of Pavement, Belly and The Breeders and they've learnt them well. The AXA25 copes superbly well with the melodic hooks and sweeping guitar riffs on this 2018 single.



### Great British Sound

What does 'British Sound' mean? To us it's about removing any barriers that might distort or alter the original recording and not adding any of our own flavour. What you hear from our products is a pure and unfiltered 'British' sound – just as the artist intended.



## Stacking Up

	AXA25	AXA35	AXR85	AXR100
POWER PER CHANNEL	25W (8 OHMS)	35W (8 OHMS)	85W (8 OHMS)	100W (8 OHMS)
ANALOGUE INPUTS	4 x RCA	4 x RCA	3 x RCA	3 x RCA
OPTICAL INPUTS	-	-	-	2
COAXIAL INPUTS	-	-	-	1
REC OUT	YES	YES	YES	YES
MM PHONO STAGE	-	YES	YES	YES
WHITE DISPLAY SCREEN	-	YES	YES	YES
3.5MM AUX-IN	YES	YES	YES	YES
HEADPHONE OUTPUT	-	YES	YES	YES
SUBWOOFER OUTPUT	-	-	YES	YES
A/B SPEAKER TERMINALS	-	YES	YES	YES
5V 500MA USB (POWER PORT ONLY)	YES	YES	-	-
FM/AM RECEIVER	-	-	YES	YES
RDS	-	-	YES	YES
BLUETOOTH	-	-	YES	YES

## Technical Specification

POWER OUTPUT:	25 watts (into 8Ω)
THD (UNWEIGHTED):	<0.015% @ 1kHz, 80% of rated power <0.15% 20Hz – 20kHz, 80% of rated power <0.1% 20Hz – 20kHz @ 10W
FREQUENCY RESPONSE (-3DB):	(-3dB) 10Hz - 30kHz
S/N RATIO (REF 1W):	>82dB (unweighted)
INPUT IMPEDANCES:	32k ohms
POWER AMP DAMPING FACTOR:	>100
MAX. POWER CONSUMPTION:	180W
BASS/TREBLE CONTROLS:	Shelving, ultimate boost/cut +/- 5.5dB @ 20Hz and 20kHz
STANDBY POWER CONSUMPTION:	<0.5W
DIMENSIONS:	83 x 430 x 340mm (3.3 x 16.9 x 13.4")
WEIGHT:	5.1kg (11.2lbs)

## Related Products

### AXA35 INTEGRATED AMPLIFIER

On top of the AXA25, the AXA35 include a boost to 35 watts of power per channel, an integrated moving magnet phono stage for turntable enthusiasts, a white LCD display screen, and a ¼ inch headphone socket for private listening sessions.



### AXR85 STEREO RECEIVER

The AXR85 boasts 85 watts of power, a built-in phono stage for connecting record players with Moving Magnet cartridges, a front panel 3.5mm input for iPod/MP3 players, built-in FM/AM radio with RDS and 30 presets and four analogue inputs for connecting all your music, AV and audio sources.

